

marantz®



SR8012 11.2 CHANNEL NETWORK AV RECEIVER WITH HEOS MUSIC STREAMING TECHNOLOGY

With unparalleled Marantz performance, the new top-of-the-line SR8012 AV receiver is made for those wanting the ultimate audio and video experience. With a fully symmetrical build, the amplifier features a single board design for its 11 identical amplifier channels, each delivering 205W per channel, for seamless surround sound integration.

Highlights

11.2 channel AV Receiver with 205W per channel
 Dolby Atmos and DTS:X (up to 7.1.4 or 9.1.2), Auro-3D
 Single board per channel power amplifier design; centrally mounted, oversized toroidal transformer; copper-plated chassis
 High performance 192kHz/32bit D/A converters for all channels
 Audyssey MultEQ XT32, LFC, Sub EQ HT, Dynamic Volume and Dynamic EQ
 Built-in WiFi with 2.4GHz/5GHz dual band support
 HEOS Music Streaming Technology with HEOS App

HEOS HOME ENTERTAINMENT SKILL

AirPlay, Bluetooth, Internet Radio, Spotify Connect, TIDAL, Deezer
 Network Streaming: DSD (2.8/5.6MHz), FLAC, ALAC and WAV support
 4K/60 Hz, 4:4:4, HDR and BT.2020, Dolby Vision compatible, HLG
 8 HDMI inputs (incl. 1 front) with full HDCP 2.2 support; 3 HDMI outputs (zone)
 eARC (Enhanced Audio Return Channel) via future firmware update
 Colour-coded speaker terminals, Setup Assistant, Marantz AVR Remote App
 Advanced Multi-Room options; 11.2ch Pre-out; RS232 Control; Crestron Connected, IP-control

Your Benefits

Enough power to fill big rooms with renowned Marantz sound
 Immersive 3D sound with effects from overhead
 High-end build-quality for the ultimate in audio performance
 Highest resolution for music and movie sound
 Delivering the ultimate equalization for your individual room
 Improved network stability especially in WiFi-crowded environments
 Comfortable control options, almost unlimited music sources, and multi-room experience with additional HEOS products

Make use of ALEXA VOICE CONTROL

Access to almost unlimited online music sources
 High Resolution audio streaming for HiFi enthusiasts
 Latest HDMI standard for future-proof compatibility
 Plenty of inputs for your digital devices; different video in different rooms
 Allows 3D audio transmission from TV via HDMI audio return channel
 Hassle-free installation, setup and operation
 Audio and video in multiple rooms; ready for 3rd Party Home Automation systems



because music matters

SR8012

11.2 CHANNEL NETWORK AV RECEIVER WITH HEOS MUSIC STREAMING TECHNOLOGY



Design and specifications are subject to change by Marantz without notice.

FEATURES	SR8012
MULTICHANNEL SURROUND	
DTS HD Master / DTS:X / DTS Neural:X	• / • / •
Dolby TrueHD / Dolby Atmos / Dolby Surround	• / • / •
Auro-3D / Auroomatic	• / •
Multichannel Stereo	•
Compressed audio Enhancer: MDAx2	•
Audyssey	MultEQ XT32 with LFC/Sub EQ HT
Audyssey Dynamic EQ / Dynamic Volume	• / •
Audyssey MultEQ Editor App support	•
NETWORK / SOURCES	
Network Audio Streaming	•
HEOS Multiroom integrated	•
Lossy formats MP3 / WMA / AAC	• / • / •
Lossless formats FLAC / ALAC / WAV	• / • / •
DSD Streaming	• (2.8 MHz / 5.6 MHz)
FLAC HD 192/24 / WAV 192/24 / ALAC 192/24	• / • / •
Gapless playback	• (FLAC, WAV, ALAC, DSD)
AirPlay audio streaming	•
Internet Radio (Tuneln)	•
Spotify Connect, Deezer, TIDAL, Napster, Soundcloud *	• / • / • / • / •
Compatible with Remote APP for Smart Phones	Android/iOS
Ethernet / Wi-Fi	• / • (dual antenna / dual band)
Network: (IP-control / update)	• / •
Front Inputs: HDMI / USB	• / •
USB Audio	•
Bluetooth	•
HDMI	
4K 60Hz 4:4:4 resolution / HDCP 2.2	• / •
eARC (Enhanced Audio Return Channel)	• (via Firmware Update)
Dolby Vision compatible / Hybrid Log Gamma (HLG)	• / •
HDMI pass through on stand-by	•
3D video pass through	•
Video conversion	CVBS / HDMI; Comp / HDMI
Videoprocessing and -scaling	1080p, 4K 60/50Hz

* This feature is not available in all countries.

INPUTS/OUTPUTS	
VIDEO	
Composite In / Out	4+1 / 2
Component In / Out	3 / 1
HDMI In / Out	7+1 / 3 (2 main + 1 zone)
AUDIO	
Analogue In / Out	6+1 / 0
Digital Optical In	2
Digital Coaxial In	2
Multichannel Pre Out	• (11.2 with 11.2 processing)
Zone audio preout	2
Subwoofer Out	2
7.1 Multichannel input	•
SPECIFICATIONS	
Number of poweramps	11
Power Output per channel	
6 ohm, 1 kHz, 1%, 1ch Drive	205 W
6 ohm, 1 kHz, 0.7%, 2ch Drive	175 W
8 ohm, 20 Hz - 20 kHz, 0.08%, 2ch Drive	140 W
Audio Signal to Noise Ratio	102 dB
GENERAL	
Available colours: Black / Silver-Gold	• / •
System Remote Control	RC038SR
Power Consumption in W	780
Power Consumption No-Sound (ECO ...on/off) in W	65 / 110
Standby Consumption in W	0.2 (with CEC 0.5)
Maximum Dimensions (W x D x H) in mm	440 x 460 x 185
Weight in kg	17.4
EAN	
EU	SR8012/N1B 4951035061008 Black
	SR8012/N1SG 4951035061015 Silvergold
UK	SR8012/T1B 4951035061022 Black
	SR8012/T1SG 4951035061039 Silvergold

Sound United Europe
A Division of D&M Europe B.V.
Beemdstraat 11
5653 MA Eindhoven
The Netherlands

The Bluetooth® word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. and any use of such marks by D&M Holdings Inc. is under license. Dolby, Dolby Atmos, and the double-D symbol are trademarks of Dolby Laboratories. DTS, the Symbol, DTS in combination with the Symbol, DTS:X, and the DTS:X logo are registered trademarks or trademarks of DTS, Inc. in the United States and/or other countries. The Spotify software is subject to third party licenses found here: www.spotify.com/connect/third-party-licenses. Other trademarks and trade names are those of their respective owners. Marantz is a trademark or registered trademark of D&M Holdings, Inc.

* All specs can be subject to change.